

How do you back transfer the projects of an operator panel
and what should you watch out for?

Operating Unit	WinCC flexible		ProTool		COM-TEXT		ProSave	Memory Card
	Transfer	Uploading	Transfer	Uploading	Transfer	Uploading	Backup/Restore	Backup/Restore
Micro Panels								
OP73 Micro	X	--	--	--	--	--	X	--
TP170 Micro	X	--	--	--	--	--	X	--
TP177 Micro	X	--	--	--	--	--	X	--
K-TP178 Micro	X	--	--	--	--	--	X	--
Mobile Panels								
Mobile Panel 170	X	X ¹⁾	X	X ²⁾	--	--	X	Compact Flash Card
Mobile Panel 177 DP	X	X ¹⁾	--	--	--	--	X	Multi Media Card
Mobile Panel 177 PN	X	X ¹⁾	--	--	--	--	X	Multi Media Card
Mobile Panel 277	X	X ¹⁾	--	--	--	--	X	Multi Media Card
Mobile Panel 277 IWLAN	X	X ¹⁾	--	--	--	--	X	Multi Media Card Secure Digital Card USB-Stick
Basic Panels								
KTP1000 Basic DP	X	--	--	--	--	--	X	--
KTP1000 Basic PN	X	--	--	--	--	--	X	--
TP1500 Basic PN	X	--	--	--	--	--	X	--
Panels								
TD10	--	--	--	--	X	X	--	--
TD17	--	--	X	--	--	--	X	--
TD20	--	--	--	--	X	X	--	--
OP3	--	--	X	--	--	--	--	--

How do you back transfer the projects of an operator panel
and what should you watch out for?

Operating Unit	WinCC flexible		ProTool		COM-TEXT		ProSave	Memory Card
	Transfer	Uploading	Transfer	Uploading	Transfer	Uploading	Backup/Restore	Backup/Restore
OP5 less FW1.20	--	--	--	--	X	X	--	--
OP5 ex FW1.20	--	--	X	--	X	X ³⁾	--	--
OP7	--	--	X	--	--	--	X	--
OP15 less FW2.20	--	--	--	--	X	X	--	--
OP15 ex FW2.20	--	--	X	--	X	X ³⁾	--	--
OP17	--	--	X	--	--	--	X	--
OP20	--	--	--	--	X	X	--	--
OP25	--	--	X	--	--	--	--	PCMCIA-Modul
OP/TP27	--	--	X	--	--	--	X	PCMCIA-Modul
OP35	--	--	X	--	--	--	--	PCMCIA-Modul
OP/TP37	--	--	X	--	--	--	X	PCMCIA-Modul
OP37 PRO	--	--	X	X ²⁾	--	--	--	Hard disc ⁴⁾
OP73	X	--	--	--	--	--	X	--
OP77A	X	--	--	--	--	--	X	--
OP77B	X	X ¹⁾	--	--	--	--	X	Multi Media Card
TP170A	X	--	X	--	--	--	X ⁵⁾	--
TP/OP170B	X	X ¹⁾	X	X ²⁾	--	--	X ⁵⁾	Compact Flash Card
TP177A	X	--	--	--	--	--	X	--
TP/OP177B mono DP	X	X ¹⁾	--	--	--	--	X	Multi Media Card
TP/OP177B color PN/DP	X	X ¹⁾	--	--	--	--	X	Multi Media Card
TP/OP270	X	X ¹⁾	X	X ²⁾	--	--	X	Compact Flash Card

Operating Unit	WinCC flexible		ProTool		COM-TEXT		ProSave	Memory Card
	Transfer	Uploading	Transfer	Uploading	Transfer	Uploading	Backup/Restore	Backup/Restore
TP/OP277	X	X ¹⁾	--	--	--	--	X	Multi Media Card
Multi Panels								
MP177	X	X ¹⁾	--	--	--	--	X	Multi Media Card Secure Digital Card USB-Stick
MP270	--	--	X	X ²⁾	--	--	X	Compact Flash Card
MP270B / MP270B Touch	X	X ¹⁾	X	X ²⁾	--	--	X	Compact Flash Card
MP277 / MP277 Touch	X	X ¹⁾	--	--	--	--	X	Multi Media Card
MP370 / MP370 Touch	X	X ¹⁾	X	X ²⁾	--	--	X ⁵⁾	Compact Flash Card
MP377 / MP377 Touch	X	X ¹⁾	--	--	--	--	X	Multi Media Card Secure Digital Card Compact Flash Card USB-Stick
PC-Systems								
PC-Runtime	X	X ¹⁾	X	X ²⁾	--	--	--	Hard disc ⁴⁾
SIMATIC C7								
C7-621 (OP3)	--	--	X	--	--	--	--	--
C7-623 (OP5)	--	--	X	--	--	--	--	--
C7-624 (OP15)	--	--	X	--	--	--	--	--
C7-626 (OP25)	--	--	X	--	--	--	--	--
C7-633 (OP7)	--	--	X	--	--	--	X	--
C7-634 (OP17)	--	--	X	--	--	--	X	--
C7-635 (TP/OP 170B)	X	X ¹⁾	X	X ²⁾	--	--	X	Compact Flash Card

How do you back transfer the projects of an operator panel
and what should you watch out for?

Operating Unit	WinCC flexible		ProTool		COM-TEXT		ProSave	Memory Card
	Transfer	Uploading	Transfer	Uploading	Transfer	Uploading	Backup/Restore	Backup/Restore
C7-636 (OP 270)	X	X ¹⁾	X	X ²⁾	--	--	X	Compact Flash Card

1)	Uploading only possible, if the Transfer of the current project file from the configuration computer to the operating unit must be performed using the Upload option " Enable backtransfer ".
2)	Uploading only possible, if the Transfer of the current project file from the configuration computer to the operating unit must be performed using the Upload option " Enable upload ".
3)	Uploading possible, if the transfer of the current project done before with COM-TEXT
4)	Ensure with the Windows-Explorer. Ensure of the FWD-file or rather FWX-file.
5)	Starting from ProTool V6