2. Memory Cartridge will be red by…

1. Memory Cartridge will be written by...

CPU Typ	CPU Release	EEPROM Capacity	EEPROM Data*	CPU 221								CPU 222								CPU 224										CPU 224 XP		CPU 226									CPU 226 XM			
				1.00	1.01	1.10	1.11	1.20	1.22	2.00	2.01	1.00	1.01	1.10	1.11	1.20	1.21	1.22	2.00	2.01	1.00	1.01	1.10	1.11	1.12	1.20	1.21	1.22	2.00	2.01	2.00	2.01	1.00	1.01	1.02	1.20	1.21	1.22	1.23	2.00	2.01	1.00	1.20	1.21	1.22
blank (New from Factory)		32K		FE	FE	FE	FE	FE	FE	C	C	FE	FE	FE	FE	FE	FE	FE	C	C	FE	FE	FE	FE	FE	FE	FE	FE	C	C	C	C	FE	FE	FE	FE	FE	FE	FE	C	C	FE	FE	FE	FE
		64K		SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
221	1.00	32K		C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.01			C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.10			C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.11			C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.20			NC	NC	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.22			NC	NC	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	2.00	32K		NC	NC	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
		64K		SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
	2.01	32K		SU	SU	SU	SU	SU	SU	C	C	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
		64K		SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
222	1.00	32K		NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.01			NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.10			NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.11			NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.20			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.21			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.22			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	2.00	32K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
		64K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
	2.01	32K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
		64K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
224	1.00	32K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.01			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.10			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.11			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.12			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.20			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.21			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.22			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	2.00	32K	8192 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
			8192 L 5121 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
			8193 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
		64K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
	2.01	32K	8192 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
			8192 L 5121 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
			8193 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
		64K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	C	C	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
224 XP	2.00	64K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
	2.01	64K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
226	1.00	32K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.01			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.02			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.20			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.21			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.22			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	1.23			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
	2.00	32K	8192 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
			8192 L 5121 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
			8193 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
			16384 L 10240 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
			16385 L 10240 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	NC	NC	NC	NC
		64K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	NC	NC	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	NC	NC	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
	2.01	32K	8192 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C	C	C	C	C	C	C	C
			8192 L 5121 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
			8193 L 5120 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
			16384 L 10240 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
			16385 L 10240 V	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	NC	NC	NC	NC
		64K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	NC	NC	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
		256K		SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	NC	NC	SU	SU	SU	SU	SU	SU	SU	SU	NC	NC	NC	NC	SU	SU	SU	SU	SU	SU	SU	C	C	SU	SU	SU	SU
226 XM	1.00	32K		NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
	1.20			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
	1.21			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C
	1.22			NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC	C	C	C	C	C	C	C

C = compatible NC = not compatible SU = slot unfititing FE = Fatal Error * = L = max. length of user program, V = max. length of user data

Copyright © Siemens AG